

## **BACKLIT LED HOUSE NUMBERS**

### **MOUNTING INSTRUCTIONS**

- Carefully remove package place house numbers on a smooth cloth to prevent from scratching .
- Clean mount surface or wall before installation of numbers .
- There are two mount holes per house numbers, the top mount holes are horizontally aligned providing a reference for level mount .
- To determine the top end of each house number e.g. 8. 9 or 6 a small drain hole is located at the boom end keep drain hole to boom side
- Mark a level line on the mount surface /wall for the top mount holes of the house numbers series. Decide how much space you want between the each house number then use template .
- Position paper template flat on wall and put masking tape to secure template paper
- Mark drill holes using pencil or marker to mark holes indicated on the template on mounting surface. Make sure that the marks are visible on the walls on the mount surface after removing the templates .
- Drill mount holes through the marked holes of each number .
- Drill two mount holes and insert the wall anchors into the holes .
- Drill one 1/2 wiring harness hole through the wall outside in marked wire hole (usually it is marked in the middle of letter).
- Screw the threaded studs/screws into the top and bottom threaded holes on the back of each number.
- Hold the first number up to the drilled holes and gently thread the middle wiring through the wire hole to get the wire out at the back of the wall
- Gently and carefully push the thread pins/screws into the wall anchors until numbers are properly inserted to the mounting wall / surface, leaving desired space from the wall for floating effect at the back of the numbers . Do not use metal tool to push house numbers If required use a wooden smooth surface or rubber mallet to gently tap into place to avoid damaging numbers Repeat same for other numbers
- If you have more number, connect up-to 5 numbers to each other with wire connectors attached to each number (red and black wire) .
- You can connect up to 5 numbers to one power plug
- The house numbers are connected to each other with wires on the interior side of the wall ,so wirwes are not visible from front side.
- Connect the first or last number to the power adapter.
- Plug the power supply into an interior AC outlet . all numbers will be on .

### **TOOLS REQUIRED**

- Pencil or Marker
- Masking tape
- Drill Machine
- Measuring tape and Leveller
- Rubber hammer /or wood block

**NOTES :** It is the consumer's responsibility to ensure drill holes that penetrate and exterior wall are properly sealed using exterior grade caulking or any other sealing compound. Prima Backlit LED house number are not certified for commercial use and not be responsible for any damage or loss of any kind.

For more details please call TOLL FREE NUMBER 1 866 691 11 22

[www.primadecorativehardware.com](http://www.primadecorativehardware.com)